

# VarioShaker 270.

## Component separator for pick and place and flexible feeding.



Misprints and technical changes reserved. Status: 05/2021



**VARIOBOTIC**  
endless possibilities

More than just a simple component separator. The Varioshaker 270 is primarily used in the fields of pick and place and flexible feeding. In comparison to conventional systems, the VarioShaker 270 is easy to set up and configure as well as robust and uncomplicated in use. Components with different shapes can be separated by controlled movements. In addition to a web-based configuration for easy operation, the VarioShaker 270 has an I/O interface and can therefore be adapted to almost any robot.

 [www.variobotic.de](http://www.variobotic.de)



### Contact and Support

BIBUS Spain  
Antonio Fernández

 [www.bibus.es](http://www.bibus.es)

 [afv@bibus.es](mailto:afv@bibus.es)

 +34 986 247 286

**BIBUS**  
SUPPORTING YOUR SUCCESS

# VarioShaker 270.

## Technical specifications.

<b>Usable area</b>	Approx. 185 × 185 mm
<b>Material vibrating bowl</b>	POM white
<b>Vibrating bowl (transmitted light)</b>	Plain with removal bevels
<b>Recommended component size</b>	0,5 to approx. 50 mm (further part sizes possible after testing)
<b>Optional vibrating surfaces</b>	Reduced area for smaller components, grooves, holes, elevations, structure, depressions (can be customized to your application)
<b>Dimensions</b>	Approx. 400 × 340 × 127,5 mm (L x W x H)
<b>Temperature range</b>	5°C - 40°C
<b>Weight</b>	14.2 kg
<b>Software</b>	WebGUI via standard web browser

	+48 V / 2A	Power supply (combine mass from 24 V and 48 V) the fuse is located in the housing																								
	+24V / 2A																									
	0 V																									
	PE	Protective earth conductor																								
<b>Inputs 24 V DC max. 2,4 mA</b>	I_EN	Enable / Start																								
	I_Bit1	Binary coded sequence selection - examples: <table border="1" style="margin-left: 20px;"> <thead> <tr> <th></th> <th>Bit 1</th> <th>Bit 2</th> <th>Bit 3</th> <th>Bit 4</th> <th>Bit 5</th> </tr> </thead> <tbody> <tr> <td>Sequence 1:</td> <td>1</td> <td>0</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>Sequence 2:</td> <td>0</td> <td>1</td> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>Sequence 3:</td> <td>1</td> <td>1</td> <td>0</td> <td>0</td> <td>0</td> </tr> </tbody> </table>		Bit 1	Bit 2	Bit 3	Bit 4	Bit 5	Sequence 1:	1	0	0	0	0	Sequence 2:	0	1	0	0	0	Sequence 3:	1	1	0	0	0
			Bit 1	Bit 2	Bit 3	Bit 4	Bit 5																			
	Sequence 1:		1	0	0	0	0																			
	Sequence 2:		0	1	0	0	0																			
	Sequence 3:		1	1	0	0	0																			
I_Bit2																										
I_Bit3																										
I_Bit4																										
I_Bit5																										
	I_LED	Control input for transmitted light																								
<b>Outputs 24 V DC max. 100 mA</b>	O_Rdy	Condition: ready																								
	O_Bsy	Condition: busy																								
	O_Res	Unassigned (reserved)																								
	O_Bnk	Hopper on																								
<b>Output 24 V DC max. 500 mA</b>	O_Top	Incident light (additional lighting, optional)																								
<b>Further connections</b>	M12 cable (8-pin) 5m	Control line between VarioShaker and control box																								
	Ethernet (TCP/IP)	Optional for control																								
	USB	USB port for update WebGUI																								

Misprints and technical changes reserved, Status: 05/2021

